



La CCU permet une sortie UHD et HD simultanée dans un format compact. Le mode HD permet une sortie en 240p, 180p et 120p lors d'une utilisation normale.

AK-UCU600

L'unité de commande de caméra (CCU) AK-UCU600 permet la transmission par fibre optique de signaux vidéo 4K/HD non compressés sur de longues distances.

Key Features

Comprend un système dual UHD 12G-SDI, avec prise en charge QuadLink 3G-SDI et entrelacement à deux champs

Transmission par fibre optique de signaux vidéo non compressés sur une distance d'environ 2000 m entre la caméra et l'unité de commande

Prise en charge TICO via une sortie SDI (4K par 3G-SDI) ; les signaux 4K peuvent être transférés via un câble 3G-SDI conventionnel.

Sortie HDR/SDR simultanée et sortie HDR BT2020/B709 simultanée possibles

Prise en charge du streaming IP (100 Base-T)





AK-UCU600

<https://eu.connect.panasonic.com/fr/fr/broadcast-proav/accessories/ak-ucu600>

Camera Control Unit (CCU) -> General	AK-UCU600PJ/AK-UCU600PSJ 100 V - 120 V AC, 50 Hz/60 Hz
-> Power Supply	AK-UCU600EJ/AK-UCU600ESJ 100 V - 240 V AC, 50 Hz/60 Hz
Camera Control Unit (CCU) -> General	500 W (Without camera connected: 90 W)
-> Power Consumption	
Camera Control Unit (CCU) -> General	240 V AC (tolerance: 5 %), 1.46 A, 50 Hz / 60 Hz
-> Capacity for Supplying Power to a	
Camera	
Camera Control Unit (CCU) -> General	0 °C to 40 °C (32 °F to 104 °F)
-> Operating Temperature	
Camera Control Unit (CCU) -> General	10 % to 90 % (no condensation)
-> Humidity	
Camera Control Unit (CCU) -> General	Approx. 8.9 kg (19.6 lb)
-> Weight	
Camera Control Unit (CCU) -> General	W 424 mm x H 88 mm x D 401 mm (16-5/8 inches x 3-7/16 inches x 15-13/16 inches)
-> Dimensions	(excluding protrusions)
Camera Control Unit (CCU) ->	3G/HD-SDI:5 lines (embedded audio is supported only for HD signals)
Input/Output -> Video Output	12G/6G/3G/HD-SDI:2 lines
	HD-SDI:1 line (shared with picture monitor output)
	Analog composite:2 lines (1 line shared with picture monitor output ^{*1})
Camera Control Unit (CCU) ->	HD-SDI 1 line (HD TRUNK output)
Input/Output	3G/HD-SDI 1 line (PTCO output)
Camera Control Unit (CCU) ->	3G-HD/HD/SD-SDI 4 lines (RET1 input has active-through output)
Input/Output -> Return Input	Analog composite 1 line
Camera Control Unit (CCU) ->	HD-SDI 1 line (with active-through output)
Input/Output -> Prompter Input	Analog composite 2 lines (through output of 1 and input of 2 share the connector ^{*1})
	It is not terminated when the unit is turned OFF. No through output.
Camera Control Unit (CCU) ->	BB (black burst) / tri-level ^{*3} : 1 line
Input/Output -> Reference Input	(automatic termination, connect to upper connector; BB signal and tri-level ^{*3} signal automatically recognized, with loop-through output)
Camera Control Unit (CCU) ->	0 dBm/600 Ω, 2 lines (XLR, 3-pin, male)
Input/Output -> Microphone Output	Intercom input/output (ENG / PROD, 0 dBm, 600 Ω (4 W) / 1 V [p-p], 200 Ω (RTS), 4 W / RTS / CLRCOM):2 lines ^{*1}
Camera Control Unit (CCU) ->	PGM input (0 dBm/600 Ω):2 lines ^{*1}
Input/Output -> Communication	Tally input (red, green, yellow):1 input each
Camera Control Unit (CCU) ->	WFM control
Input/Output -> AUX	6-bit (open collector output ^{*1} , terminal shared with camera microphone gain setting ^{*1})
	Camera microphone gain setting input
	5-bit (photo-coupler input ^{*1} , terminal shared with WFM control ^{*1})
	Down-conversion system setting input 2-bit (photo-coupler input)
Camera Control Unit (CCU) ->	RS-422 / RS-232C 2 lines
Input/Output -> TRUNK	
Camera Control Unit (CCU) ->	RS-422
Input/Output -> ROP	1 line, 16 V DC output (only one of this and FRONT/REAR ROP can be selected at one time via the menu or the [ROP FRONT/REAR] selection switch on the front panel)
Camera Control Unit (CCU) ->	RS-422 1 line, GPI for control
Input/Output -> MSU	LAN connection with camera side via an optical cable ^{*4}
Camera Control Unit (CCU) ->	1 line, 100BASE-TX, 1000BASE-T
Input/Output -> LAN TRUNK	Personal computer connection for distribution via the Web ^{*4}
Camera Control Unit (CCU) ->	1 line, 10BASE-T, 100BASE-TX (use a crossover cable when connecting directly with a personal computer)
IP/12G/3G Interface Kit AK-NP600G ->	0 °C to 40 °C (32 °F to 104 °F)
General -> Operating Temperature	
IP/12G/3G Interface Kit AK-NP600G ->	10% to 90% (no condensation)
General -> Operating Humidity	
IP/12G/3G Interface Kit AK-NP600G ->	Approx. 284 g (0.63 lbs) (including radiator fins)
General -> Weight	
IP/12G/3G Interface Kit AK-NP600G ->	W 175.5 mm x H 28.8 mm x D 138.5 mm
General -> Dimensions	(6-29/32 inches x 1-1/8 inches x 5-7/16 inches)

IP/12G/3G Interface Kit AK-NP600G - BNC x 1, 12G / 6G / 3G / 1.5G HD SDI : 0.8 V [p-p], 75 Ω
> Input/Output - > < UHD/HS/HD SDI
OUT1 > terminal
IP/12G/3G Interface Kit AK-NP600G - BNC x 1, 12G / 6G / 3G / 1.5G HD SDI: 0.8 V [p-p], 75 Ω
> Input/Output - > < UHD/HS/HD SDI
OUT2 > terminal
IP/12G/3G Interface Kit AK-NP600G - BNC x 1, 3G / 1.5G HD SDI: 0.8 V [p-p], 75 Ω
> Input/Output - > < UHD/HS/HD SDI
OUT3 > terminal
IP/12G/3G Interface Kit AK-NP600G - BNC x 1, 3G / 1.5G HD SDI: 0.8 V [p-p], 75 Ω
> Input/Output - > < UHD/HS/HD SDI
OUT4 > terminal
IP/12G/3G Interface Kit AK-NP600G - BNC x 1, 1.5G HD SDI when HD TRUNK, 3G / 1.5G HD SDI when TICO : 0.8 V [p-p], 75 Ω
> Input/Output - > < HD TRUNK/TICO
OUT > terminal
IP/12G/3G Interface Kit AK-NP600G - BNC x 1, 1.5G HD SDI: 0.8 V [p-p], 75 Ω
> Input/Output - > < HD SDI/PROMPT
IN > terminal
IP/12G/3G Interface Kit AK-NP600G - SFP+ x 1, 10GBASE-LR
> Input/Output - > < SFP+1 > slot
IP/12G/3G Interface Kit AK-NP600G - SFP+ x 1, 10GBASE-LR
> Input/Output - > < SFP+2 > slot
IP/12G/3G Interface Kit AK-NP600G - RJ-45 x 1
> Input/Output - > < LAN2 > terminal
IP/12G/3G Interface Kit AK-NP600G ->Pillar (M3 x H20) x 1, Options rear panel x 1, Power cable x 1, Heat-transfer sheet x 1, Bundled Items askets x 2

Footnote Description

Depending on the setting, only one of them can be selected at one time.

For details on output formats, please see the "Supported formats".

The BB (black burst) signal and tri-level sync signal of the reference input are recognized automatically.

IP video cannot be transmitted when [CCU MODE] is set to [2160/23.98p], [2160/23.98PsF], [1080/23.98p], or [1080/23.98PsF].